

Product Summary

V _{(BR)DSS}	R DS(on)TYP	ID
-30V	45mΩ@-10V	-4.1A
-307	57mΩ@-4.5V	-4.1A

Feature

- Trench Technology Power MOSFET
- Low R_{DS(ON)}
- Low Gate Charge
- Low Gate Resistance

Application


- Load Switch
- PWM Applications

MARKING:



ABSOLUTE MAXIMUM RATINGS (T_A = 25^{\circ}C unless otherwise noted)

Parameter	Symbol	Value	Unit	
Drain - Source Voltage	V _{DS}	-30	V	
Gate - Source Voltage	Vgs	±20	V	
Continuous Drain Current ^{1,5}	T _A = 25℃	lь	-4.1	А
Pulsed Drain Current ²		Ідм	-16	А
Power Dissipation ^{4,5}	T _A = 25℃	PD	1.4	W
Thermal Resistance from Junction to Ambient ⁵		Reja	89	°C/W
Junction and Storage Temperature Range		TJ,TSTG	-55~ +150	°C



德方代理|原装正品 07 www.coon REASUNOS

RS3407E P-Channel MOSFET

Parameter	Symbol	Test Condition	Min	Туре	Max	Unit
Off Characteristics	•	•		•		
Drain - Source Breakdown Voltage	V _{(BR)DSS}	V _{GS} = 0V, I _D = -250µA	-30			V
Zero Gate Voltage Drain Current	IDSS	V _{DS} = -24V, V _{GS} = 0V			-1	μA
Gate - Body Leakage Current	I _{GSS}	$V_{GS} = \pm 20 V$, $V_{DS} = 0 V$			±100	nA
On Characteristics ³			•	-		
Gate Threshold Voltage	V _{GS(th)}	$V_{DS} = V_{GS}, I_D = -250 \mu A$	-1	-1.6	-3	V
Drain-source On-resistance	Deres	V _{GS} = -10V, I _D = -4.1A		45	60	
	R _{DS(on)}	V _{GS} = -4.5V, I _D = -3A		57	80	mΩ
Forward Transconductance	g FS	V _{DS} = -5V, I _D = -4A	5			S
Dynamic Characteristics			•	-		
Input Capacitance	Ciss			572		
Output Capacitance	Coss	V _{DS} = -15V, V _{GS} = 0V, f = 1MHz		65		pF
Reverse Transfer Capacitance	Crss	1		57		
Switching Characteristics						
Total Gate Charge	Qg			10		
Gate-source Charge	Qgs	V _{DS} = -15V, V _{GS} = -10V, I _D = -4.1A		2		nC
Gate-drain Charge	Q _{gd}	1		3.4		
Turn-on Delay Time	t _{d(on)}			8		
Turn-on Rise Time	tr	V _{DD} = -15V, V _{GS} = -10V,		6.2		
Turn-off Delay Ttime	t _{d(off)}	R _L = 3.65Ω, R _G = 3Ω		25		ns
Turn-off Fall Time	t _f]		10		
Source - Drain Diode Characteristics						
Diode Forward Voltage ³	V _{DS}	V _{GS} = 0V, I _S = -2A			1.2	V

Notes :

1. The maximum current rating is limited by package.

2.Pulse Test : Pulse Width \leq 10µs, duty cycle \leq 1%.


3.Pulse Test : Pulse Width \leq 300µs, duty cycle \leq 2%.


4. The power dissipation P_D is limited by $T_{J(MAX)} = 150^{\circ}C$.


5.Device mounted on $1in^2$ FR-4 board with 2oz. Copper, in a still air environment with T_A =25°C.





Typical Characteristics

















SOT-23 Package Information




Symbol	Dimensions	In Millimeters	Dimensions In Inches		
cymbol	Min.	Max.	Min.	Max.	
А	0.900	1.150	0.035	0.045	
A1	0.000	0.100	0.000	0.004	
A2	0.900	1.050	0.035	0.041	
b	0.300	0.500	0.012	0.020	
С	0.080	0.150	0.003	0.006	
D	2.800	3.000	0.110	0.118	
E	1.200	1.400	0.047	0.055	
E1	2.250	2.550	0.089	0.100	
е	0.950	REF.	0.037	REF.	
e1	1.800	2.000	0.071	0.079	
L	0.550	REF.	0.022	REF.	
L1	0.300	0.500	0.012	0.020	
θ	0°	8°	0°	8°	



SOT-23 Tape and Reel


SOT-23 Tape and reel


SOT-23 Embossed Carrier Tape



Dimensions are in millimeter										
Pkg type	A	в	с	d	E	F	PO	Р	P1	w
SOT-23	3.15	2.77	1.22	Ø1.50	1.75	3.50	4.00	4.00	2.00	8.00

SOT-23 Tape Leader and Trailer





Dimensions are in millimeter								
Reel Option	D	D1	D2	G	Н	L	W1	W2
7"Dia	Ø178.00	54.40	13.00	R78.00	R25.60	R6.50	9.50	12.30

REEL	Reel Size	Box	Box Size(mm)	Carton	Carton Size(mm)	G.W.(kg)
3000 pcs	7 inch	30,000 pcs	203×203×195	120,000 pcs	438×438×220	

Copyright Reasunos

REV: A0 AUG. 2022



Disclaimers:

Reasunos Semiconductor Technology CO.,LTD(Reasunos)reserves the right to make changes without notice in order to improve reliability,function or design and to discontinue any product or service without notice .Customers should obtain the latest relevant information before orders and should verify that such information in current and complete.All products are sold subject to Reasunos's terms and conditions supplied at the time of orderacknowledgement.

Reasunos Semiconductor Technology CO.,LTD warrants performance of its hardware products to the speciffications at the time of sale.Testing,reliability and quality control are used to the extene Reasunos deems necessary to support this warrantee. Except where agreed upon by contractual agreement,testing of all parameters of each product is not necessarily performed.

Reasunos Semiconductor Technology CO.,LTD does not assume any liability arising from the use of any product or circuit designs described herein.Customers are responsible for their products and applications using Reasunos's components.To minimize risk,customers must provide adequate design and operating safeguards.

Reasunos Semiconductor Technology CO.,LTD does not warrant or convey any license either expressed or implied under its patent rights,nor the rights of others.Reproduction of information in Reasunos's data sheeets or data books is permissible only if reproduction is without modification oralteration.Reproduction of this information with any alteration is an unfair and deceptive business practice. Reasunos Semiconductor Technology CO.,LTD is not responsible or liable for such altered documentation.

Resale of Reasunos's products with statements different from or beyond the parameters stated by Reasunos Semiconductor Technology CO.,LTD for that product or service voids all express or implied warrantees for the associated Reasunos's product or service and is unfair and deceptive business practice. Reasunos Semiconductor Technology CO.,LTD is not responsible or liable for such statements.

Life Support Policy:

Reasunos Semiconductor Technology CO.,LTD's Products are not authorized for use as critical components in life support devices or systems without the expressed written approval of Reasunos Semiconductor Technology CO.,LTD.

As used herein:

- 1. Life support devices or systems are devices or systems which:
 - a.are intended for surgical implant into the human body,
 - b.support or sustain life,
 - c.whose failuer to when properly used in accordance with instructions for used provided in the laeling,can be reasonably expected to result in significant injury to the user.
- 2.A critical component is any component of a life support device or system whose failure to system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.